

LRS-LC

LOGIC CONTROLLER

Applications

The LRS-LC Logic Interface works with LRS-DB Direct Burial or LRS-FP Flat Pack magnetoresistive sensors. The Logic Controller expands the functionality of the sensors by providing additional features and application specific logic operations to meet the needs of more demanding installations.

The Logic Controller allows one or two sensors to be connected and provides 6 logic functions and 2 separate relay outputs. Once the sensor(s) has been programmed using the LRS-C1 Control Unit, the sensor(s) store the settings and operate independent of the Control Unit and can be connected to the Logic Controller.

The LRS sensor provides up to a 5ft. sensing range in all directions. The LRS-LC Logic Controller allows 2 sensors to be connected with one output to extend the detection area up to 20ft. Also, A/B directional logic can be selected with an output for each direction of travel as a vehicle passes over two sensors.

The status LEDs and durable housing with a standard 11-pin plug-in socket makes installation quick and easy.

LRS-LC



EMX Industries, Inc.

4564 Johnston Parkway, Cleveland, Ohio 44128

P. 800 426 9912 F. 216 518 9884

Sales Inquiries: salesupport@emxinc.com **Technical Support:** technical@emxinc.com


www.emxinc.com

LOGIC FUNCTIONS

- Two relay operation
- A/B directional logic
- Pulse on entry
- Pulse on exit
- Double relay
- Relay 1 only



LRS-LC



LD-11B

Technical Data

Power indicator	Green LED
Detect indicator	2 Red LEDs
Configuration selector	10 position rotary switch
Outputs	Relay 1: SPDT (form C) Relay 2: SPST (form A)
Output ratings	1A @ 24 VDC/120 VAC
Operating environment	-40° C...82° C (-40° F...180° F) 0...95% relative humidity
Housing material	ABS
Enclosure	IP30
Power	12-30 VDC and 24 VAC
Operating current (standby/detect)	One sensor connected: 22/35mA Two sensors connected: 33/60mA
Supply protection circuitry	Reverse polarity and fuse protected
Dimensions	73mm (2.9") x 38mm (1.2") x 78mm (3.1")
Weight	0.25 lbs. (113 g)
Connector	11 pin male connector (JEDEC B11-88)

Ordering Information

- LRS-LC Logic Interface, includes black 11 pin socket base DIN rail mount

WARRANTY EMX INC. the product described herein for a period of 2 years under normal use and service from the date of sale to our customer. The product will be free from defects in material and workmanship. This warranty does not cover ordinary wear and tear, abuse, misuse, overloading, altered products, or damage caused by the purchaser from incorrect connections, or lightning damage. There is no warranty of merchantability. There are no warranties expressed, implied or any affirmation of fact or representation which extend beyond the description set forth herein. EMX Inc. sole responsibility and liability, and purchaser's exclusive remedy shall be limited to the repair or replacement at EMX's option of a part or parts not so conforming to the warranty. In no event shall EMX Inc. be liable for damages of any nature, including incidental or consequential damages, including but, not limited to any damages resulting from non-conformity defect in material or workmanship. Rev 1.3 01/25/19

